

## **LA100 Application Note 3: Conversion of a Rack mount unit to two separate units**

**Use CV2 Conversion Kit, the contents are as follows:-**

- 2 x Top Covers.
  - 2 x Bottom Covers.
  - 16 x M3 x 6 countersunk pozidriv black screws.
  - 2 x Stands.
1. Remove rack mount endplates from the unit.
  2. Remove the top and bottom covers.
  3. Remove the four M4x12 stainless steel nut and bolt sets and the two aluminium spacing holding the units together.
  4. Place new covers on the separate units ensuring that the top cover with a blanked off speaker grille is fitted to the LA101. DO NOT over tighten the screws.
  5. Fit the stands. On some chassis there is a choice of two holes into which the end of the stands can be located. If this is the case, use the rearmost holes.

WAB 02.05.1989